



ISTRUZIONI INSTALLAZIONE - INSTALLING INSTRUCTIONS - INSTRUCTIONS DE MONTAGE



- ① Remove the decorative frontal panel using a screwdriver on all four sides.

Rimuovere il pannello decorativo frontale utilizzando un cacciavite sui quattro lati.




- ② Unscrew the nut with the provided key for at least 10 mm and remove the four bracket inside the lamp.

LEAVE THE SCREW IN THE HOLE!


Svitare le quattro viti con la chiave fornita per almeno 10 mm e rimuovere le quattro staffe.

LASCIARE LA VITE NEL FORO!





- ③ Connect the wiring cables following the sketch. (DALI DIMMING SYSTEM)

Connettere i cavi della corrente seguendo lo schema. (DIMMERAZIONE DALI)



- ④ Lift the lamp upwards into the ceiling hole and insert the brackets precedently removed. Fasten the brackets with the key.

Sollevare la lampada nel foro a soffitto e inserire le staffe precedentemente rimosse. Fissare le staffe con la chiave.



- ⑤ Fix the decorative frontal panel pushing the pins in the springs.


Fissare il pannello decorativo frontale spingendo i perni nelle molle.

ISTRUZIONI INSTALLAZIONE - INSTALLING INSTRUCTIONS - INSTRUCTIONS DE MONTAGE



Installation / wiring

Circuit diagram



Wiring type and cross section

The wiring can be in stranded wires with ferrules or solid with a cross section of 0.2–1.5 mm².


Strip 8.5–9.5 mm of insulation from the cables to ensure perfect operation of the push-wire terminals.

Use one wire for each terminal connector only.

Use each strain relief channel for one cable only.


LED module/LED Driver/supply

wire preparation:
0.2 – 1.5 mm²




Loose wiring

Press down the “push button” and remove the cable from front.



Wiring guidelines

- The cables should be run separately from the mains connections and mains cables to ensure good EMC conditions.
- The LED wiring should be kept as short as possible to ensure good EMC. The max. secondary cable length is 2 m (4 m circuit), this applies for LED output as well as for I-select 2.



For wiring in dimming operation with ready2mains refer to the ready2mains Gateway datasheet.